



F1/F2/F3/F4/F4⁺/F5

FingerTip Pulse Oximeter



Patient Monitor

Main features

- OLED single display (F2/F5), dual-color LCD display, brightness 4-level adjustable (F1/F3/F4/F4⁺)
- 4-direction readings automatically (F1) or manually (F4/F4⁺)
- 6 display modes (F1/F4/F4⁺)
- Display of SpO2, PR, SpO2 bar graph, PR waveform (F1/F3/F4/F4⁺)
- Special design for children or neonates (F3)
- Auto-OFF after 8 seconds (F1/F2/F3/F4/F5) or 16 seconds (F4⁺) without operation
- Alarm volume adjustable (F4⁺)
- Setup memory for preserving last setting (F4⁺)
- Beep sound on/off selectable (F4⁺)
- Visual alarm of low battery capacity
- Less than 0.4% perfusion

F1/F2/F3/F4/F4⁺/F5

FingerTip Pulse Oximeter



Specifications

SpO2 Measuring Range:	0% - 100%;
Pulse Rate Measuring Range:	30 bpm - 250 bpm;
Pulse Wave Display:	columniation display and or waveform display
Power Requirements:	2.6V~3.6V
Power Consumption:	< 30mA
Resolution	
SpO2:	1%
1 Pulse Rate:	1bpm
Measurement Accuracy	
SpO2,:	±2% in stage of 70%-100% no definition when stage is below 70%
Pulse Rate:	±2 bpm or ±2% (select larger)
SpO2 error:	±4%
Pulse Rate error:	±2 bpm or ±2% (select larger)
Resistance to surrounding light:	≤1%
Auto power-off:	within 5s when no finger detected



Standard configuration

F1/F2/F3/F4/F4⁺/F5/ main unit
 Disposable alkaline batteries (2 PCS)
 Rechargeable button lithium battery (F3 only)
 String



Shenzhen Carewell Electronics Co., Ltd.

Add: Building 29, District B, Tanglang Industrial Zone, Taoyuan Street Nanshan, Shenzhen 518055, P.R. China
 Tel: +86-755-8617 0389 Fax: +86-755-8617 0478
 E-mail: market@carewell.com.cn Website: www.carewell.com.cn

※ Specification subject to change without prior notice

